

DoseRAE Pro

Rugged Electronic Dosimeter for Personal Radiation Dosage Monitoring



DoseRAE Pro is a rugged, compact, direct-reading and alarming electronic personal radiation detector and dosimeter. It uses a diode and a scintillation crystal to detect X- ray and gamma radiation, and provides real-time monitoring of personal dose and dose-rate allowing immediate action to reduce personal radiation exposure. DoseRAE Pro includes a Stay-time countdown timer with warning alarm to allow the user to set a specific time limit when working in a radiation area, limiting the users personal radiation exposure.

in a rugged, compact package

• Wide dose rate range and energy

Dosimeter and PRD functionality

- Wide dose rate range and energy range maximizes personal protection
- Fast response time to immediately detect radiation threats
- Ease of use minimizes personnel training & support costs and reduces total cost of ownership

KEY FEATURES

- Rugged electronic dosimeter with high sensitivity Csl Scintillator sensor
- Multiple units with reader and software can be used as a dosimetry system
- Continuous LCD digital dose rate readout in Sv/h or R/h
- Continuously accumulated total dose readout in Sv or R
- Prominent visible, audible, and vibration alarms
- User configurable Stay-Time countdown timer and alarms to prevent excessive radiation exposure
- Fast near field communication wireless data transfer
- Long calibration life
- Simple two button operation and programming

APPLICATIONS

- Nuclear power plants
- Environmental survey and clean-up
- Fire Departments
- Hazardous Material Response Teams
- Police
- EMS
- Military
- Industrial safety
- Waste management
- Hospitals and Medical Clinics



Fast dosimeter programming and data download via robust wireless Near Field Communications to the optional Dosimeter Reader







DoseRAE Pro



Rugged Electronic Dosimeter for Personal Radiation Dosage Monitoring

SPECIFICATIONS

Sensors		
Gamma Sensors	Csl (TI) + photodiode (low environment radiation)	
	Energy-compensated PIN diode (level of radiation protection)	
Dose Rate Range	$0.01\mu Sv/h$ to $9.99Sv/h$ (1 $\mu R/h$ to $999R/h$)	
Accuracy of	±20% (from 10 μSv/h to 9.99 Sv/h or from 1mR/h to 999 R/h)	
Dose Rate	$\pm 30\%$ (from 0.01 $\mu Sv/h$ to 10 $\mu Sv/h$ or 1 $\mu R/h$ to 1 mR/h)	
Dose Range	0.01μSv to 9.99Sv (1μR to 999R)	
Dose Accuracy	±15%	
Energy Range	50 keV to 6 MeV for X- and gamma radiations	
Alarms		
Alarm Alerts	• Loud audible buzzer (85+dB @ 30 cm/12")	
	Highly visible LED lights	
	Built-in vibration alarm Each alarm individually enabled/disabled	
Alarm Cattings		
Alarm Settings	 Dose: continuously adjustable: 1 µSv to 9.99 Sv (100 µR to 999 R) Dose Rate: continuously adjustable: 1 µSv/h to 9.99 Sv/h (100 µR/h to 999 R/h) 	
	• Stay Time: 1 to 999 min.	
	• "Chirp" alarm: 1 beep per accumulated dose increment (1 µSv to 9.99Sv or	
	100μR to 999R)	
	All alarm settings are passcode protected with 3 digit code Low battery alert when 48 hours of life remain	
Datalannian and C	-	
Datalogging and C Data Storage	3000 points	
Datalog Interval	User programmable, from 30 to 3,600 seconds	
Communication	Near-field Communications to optional PRR-1 Dosimeter Reader for datalog	
Communication	download, dosimeter programming, factory configuration, calibration and	
	firmware upgrade	
Power		
Battery	1 AA alkaline battery, easily accessible with a coin	
Operating Hours	750 hours of continuous use	
Operating Environ	ment	
Temperature	Operating: -20° to +50°C (-4° to +122°F)	
	Storage: -30° to +70°C (-22° to +158°F)	
Humidity	5 to 95%, non-condensing	
Shock Resistance	Drop tested from 1.5m (4.9 ft.) onto hardwood surface	
IP Rating	IP-54	
Physical Characte	eristics	
Display	LCD display with pushbutton backlight	
	Three-digit floating-point readout	
	Dose and dose rate, autoranging in units of μSv, mSv, or Sv (μR, mR, or R)	
Direct Readout		
Direct Readout User Interface	2 buttons	
User Interface	2 buttons	

DOSERAE PRO KIT INCLUDES:

- DoseRAE Pro electronic personal dosimeter with belt clip
- Alligator clip
- 1 AA battery
- User manual on CD
- Quick-start user guide
- Calibration and test certificate
- Warranty/registration card

Optional Equipment:

 PRR-1 DoseRAE Pro Dosimeter Reader and software

ORDERING INFORMATION ((MODEL PRM-1300)

Product	Part Number
DoseRAE Pro Dosimeter Kit—US version (display unit: R)	R04-0002-000
DoseRAE Pro Dosimeter Kit—EU version (display unit: Sv)	R04-0001-000

CORPORATE HEADQUARTERS

RAE Systems, Inc. 3775 North First Street San Jose, CA 95134 USA **WORLDWIDE SALES OFFICES**

 USA/Canada
 1.877.723.2878

 Europe
 +45.86.52.51.55

 Middle East
 +00971.4.440.5949

 China
 +86.10.5885.8788-3000

 Asia Pacific
 +852.2669.0828